



# Information Sheet



## Pocket Toner® NX8 Deluxe Kit

Identify and test virtually any type of wire or cable with the most adapters of any kit

### What's In the Kit:

- |                                 |                                       |
|---------------------------------|---------------------------------------|
| Pocket Toner® NX8               | RCA-male adapter                      |
| 8 ID caps                       | RCA-female adapter                    |
| 66 block adapter                | F-female coupler (F-81)               |
| RJ-11 adapter                   | F-male coupler (F-71)                 |
| RJ-45 adapter                   | F-female coupler ( <i>Speed 81™</i> ) |
| Dial Tone Detective™            | F-male push-on adapter                |
| Alligator clips & RJ-45 adapter | AAA battery                           |
| BNC-male adapter                | Deluxe case with belt clip            |
| BNC-female adapter              |                                       |



PTNX8 Deluxe has the advantage of containing the primary audio/video adapters affording versatility to test all of your home theater, audio, TV, and telephone systems. This is simply the most comprehensive kit available - perfect for complex audio/video installers.

PTNX8 is the best tone and tag tool for testing continuity, shorts, 50-75 Ω termination, and polarity—on eight cables at once! Simply place each of the numbered ID caps on the remote ends of the cables to test then connect the main unit to the other end of the test cables one at a time. If there is continuity, the green LED on the ID cap will light and the main unit will show the ID cap's number (1-8) on its digital display. In addition, the audible indicator in the main unit will emit a short tone. PTNX8 also tests for the presence of both AC and DC voltages from 6v-48v.

### FEATURES

- Low-voltage circuit protection (6v -48v) in main unit, toner unit & ID caps
- Patented Gale Corporation adapters to test any wire or cable
- 8-Segment LED displays 5 different test results
- Audible indicators in both Main Unit & detachable Toner Unit
- LED indicators on all ID caps indicate continuity
- Main Unit "beeps" when line condition changes
- Test up to 8 cables at once
- Bi-gender Toner Unit w/removable *Speed 81™* coupler
- Removable push-on F-type connector
- Nickel-plated brass connection fittings
- Lightweight and durable, anodized aluminum construction
- Push-button power switch w/dust seal
- Auto shut-off feature extends battery life
- Key high-wear parts are replaceable
- Uses 1 standard AAA battery
- One-year limited warranty



Test Result Display	
	Blinking [-] indicates an open circuit
	Blinking [5] indicates a short
	Solid [7] indicates continuity with either a 50-75 ohm ID cap or the toner unit
	A solid matching number indicates continuity with one of the 8 ID caps
	Blinking [⚡] indicates AC voltage (>6 volts)
	Solid [⚡] indicates DC voltage (>6 volts)

### Gale Corporation

P.O. Box 417280 Sacramento, CA 95841 | 888.566.5728 | [info@galecorp.com](mailto:info@galecorp.com) | [www.galecorp.com](http://www.galecorp.com)

Part #: PTNX8-DLX  
Price: \$105.95