



Information Sheet



Pocket Toner® NX8 LAN Pro Kit

Quick and accurate multi-wire identification and advanced testing for LAN systems

What's In the Kit:

- | | |
|---------------------------------|---------------------------------------|
| Pocket Toner® NX8 | BNC-female adapter |
| 8 ID caps | F-female coupler (F-81) |
| 66 block adapter | F-male coupler (F-71) |
| RJ-11 adapter | F-female coupler (<i>Speed 81™</i>) |
| 8 RJ-45 adapters | F-male push-on adapter |
| Dial Tone Detective™ | AAA battery |
| Alligator clips & RJ-45 adapter | Deluxe case with belt clip |
| BNC-male adapter | |



PTNX8 LAN Pro is equipped with the essential network adaptors (R-J45) to facilitate multiple-jack testing up to 8 at one time. When using Gale Corporation's exclusive ID caps the LED on each ID cap will illuminate when network voltage is present, this provides valuable information for all installation and service technicians.

PTNX8 is the best tone and tag tool for testing continuity, shorts, 50-75 Ω termination, and polarity—on eight cables at once! Simply place each of the numbered ID caps on the remote ends of the cables to test then connect the main unit to the other end of the test cables one at a time. If there is continuity, the green LED on the ID cap will light and the main unit will show the ID cap's number (1-8) on its digital display. In addition, the audible indicator in the main unit will emit a short tone. PTNX8 also tests for the presence of both AC and DC voltages from 6v-48v.

FEATURES

- Low-voltage circuit protection (6v -48v) in main unit, toner unit & ID caps
- Patented Gale Corporation adaptors to test any wire or cable
- 8-Segment LED displays 5 different test results
- Audible indicators in both Main Unit & detachable Toner Unit
- LED indicators on all ID caps indicate continuity
- Main Unit "beeps" when line condition changes
- Test up to 8 cables at once
- Bi-gender Toner Unit w/removable *Speed 81™* coupler
- Removable push-on F-type connector
- Nickel-plated brass connection fittings
- Lightweight and durable, anodized aluminum construction
- Push-button power switch w/dust seal
- Auto shut-off feature extends battery life
- Key high-wear parts are replaceable
- Uses 1 standard AAA battery
- One-year limited warranty



Test Result Display

	Blinking [-] indicates an open circuit
	Blinking [5] indicates a short
	Solid [7] indicates continuity with either a 50-75 ohm ID cap or the toner unit
	A solid matching number indicates continuity with one of the 8 ID caps
	Blinking [⚡] indicates AC voltage (>6 volts)
	Solid [⚡] indicates DC voltage (>6 volts)

Gale Corporation

P.O. Box 417280 Sacramento, CA 95841 | 888.566.5728 | info@galecorp.com | www.galecorp.com

Part #: PTNX8-LAN-PRO

Price: \$117.49